Ürün Hakkında

Aksa power generation system, providing optimum performance, and reliability, for stationary standby, prime power, and continuous duty applications. All generator sets are factory build, and production tested.

Güç

3 Phase,50 Hz, PF 0.8

Voltaj (V)	STANDBY GÜÇ(ESP)		PRIME GÜÇ (PRP)		STANDBY AKIM (A)
	kW	kVA	kW	kVA	
400 / 231	11,6	14,5	10.40	13	21

STANDBY RATING (ESP) Güvenilir bir şebeke kaynağının güç kesintisi süresince değişken elektrik yüküne güç sağlamak için geçerlidir. ESP, ISO 8528-1'e uygundur. Aşırı yüklemeye izin verilmez.

PRIME RATING (PRP) Değişken elektrik yüküne sınırsız saat boyunca güç sağlamak için geçerlidir. PRP, ISO 8528-1'e uygundur. %10 aşırı yük kapasitesi, 12 saatlik çalışma süresi içinde 1 saatlik bir süre için kullanılabilir.

Genel Özellikler

Model Adı	AP 15
Frekans (Hz)	50
Yakıt Tipi	Diesel
Motor Marka ve Modeli	Perkins 403A-15G1
Alternatör Marka ve Modeli	Mecc Alte ECP 3-2L/4 C
Kontrol Panel Modeli	DSE 6120
Kabin Modeli	AK 10
Ses Seviyesi @1m , @7m (dB(A))	75.6 / 66.5

Motor Özellikleri

Genel Bilgiler

Üretici	Perkins
Motor Modeli	403A-15G1
Silindir Sayısı / Tipi	3 cylinders - in line
Bore mm (in)	84

Üretici haber vermeksizin model, teknik özellikler, renk, donanım ve aksesuarlarda değişiklik yapma hakkını saklı tutar.

02/08/2026

Stroke mm (in)	90
Hacim l (cu. In)	1.496
Sıkıştırma Oranı	22.5:1
Motor Hızı (rpm)	1500
Standby Güç (kW/hp)	13.5/18.09
Prime Güç (kW/hp)	12.2/16.35
Blok Isıtıcı (Adt)	1
Blok Isıtıcı Gücü (Watt)	250
Governor Sistemi	Mechanic
Hava Filtresi	Dry Type
Hava Emiş	Naturally Aspirated

Yağlama Sistemi

Yağ Kapasitesi l (qal)	6.0
Maks. Yağ Sıcaklığı ºC (F)	135

Yakıt Sistemi

Yakıt Tipi	Diesel
Enjeksiyon Tipi	Indirect
Yakıt Pompa Tipi	Zexel Cassette type - In-Line

Elektrik Sistemi

Çalışma Voltajı (Vdc)	12 Vdc
Akü ve Kapasite (Adt/Ah)	1x36
Şarj Alternatörü (A)	15

Soğutma Sistemi

Soğutma Metodu	Water Cooled
Soğutma Suyu Kapasitesi (yalnızca motor)l (gal)	2.6

Egzoz Sistemi

Egzoz Gaz Debisi (m^3/dk)	2.9
Egzoz Geri Basınç in-Hg (kPa)	10.2
Egzoz Gaz Sıcaklığı ºC (F)	490
Egzoza Geçen Isı kW (BTU/min)	10.3

Radyatör

Toplam Soğutma Suyu Kapasitesi (l)	6
Soğutma Fan Hava Debisi m^3/min (ft^3/min)	36.6
Soğutma Havası Harici Direnç (Pa)	125

Üretici haber vermeksizin model, teknik özellikler, renk, donanım ve aksesuarlarda değişiklik yapma hakkını saklı tutar.

02/08/2026

Yakıt Tüketimi

%100 Prime Yükte Yakıt Tüketimi l/h (kg/h)	3.67
%75 Prime Yükte Yakıt Tüketimi l/h (kg/h)	2.79
%50 Prime Yükte Yakıt Tüketimi l/h (kg/h)	2.04

Alternator Özellikleri

Üretici	Mecc Alte
Alternatör Model	ECP 3-2L/4 C
Frekans (Hz)	50
Güç (kVA)	13.5
Voltaj (V)	400
Faz	3
A.V.R.	DSR
Voltaj Regülasyon	1
Yalıtım Sınıfı	H
Koruma Sınıfı	IP23
Nominal Güç Faktörü	0.8
Toplam Generator Ağırlık (kg)	87
Soğutma Havası (m³/dk)	3

Açık Jeneratör Boyutları

Uzunluk mm	1250
Genişlik mm	850
Yükseklik mm	1068
Açık Gen.Set Brüt Ağırlık, Kuru kg	425
Yakıt Tank Kapasitesi (l)	50

Kabin Özellikleri

Uzunluk mm	1851
Genişlik mm	910
Yükseklik mm	1180
Kuru Ağırlık kg	565
Yakıt Tank Kapasitesi (l)	50

Kontrol Paneli

Üretici	DSE
Kontrol Modül Modeli	DSE 6120

Üretici haber vermeksizin model, teknik özellikler, renk, donanım ve aksesuarlarda değişiklik yapma hakkını saklı tutar.

02/08/2026

İletişim Portları	CANBUS

1. Menu navigation buttons
2. Close mains button
3. Main Status and instrumentation display
4. Alarm LED's
5. Close generator button
6. Status LED's
7. Operation selecting buttons

Standart Cihazlar

DSE model 6120, Auto Mains Failure control module, Static battery charger input 198-264 volt, output 27,6V 5A (24V) or 13,8 Volt 5A (12V), fuses for control circuits. This Control Module is suitable for a wide variety of single gen-set applications

Kontrol Ünitesi

- The DSE 6120 module has been designed to monitor generator frequency, volt, current, engine oil pressure, coolant temperature running hours and battery volts.
- Module monitors the mains supply and control the switch over to the generator when the mains power fails.
- The DSE6120 also indicates operational status and fault conditions, Automatically shutting down the Gen. Set and giving true first up fault condition of Gen. Set failure.The LCD display indicates the fault.

Yapım ve Boya

Components installed in sheet steel enclosure. Phosphate chemical, pre-coating of steel provides corrosion corrosion-resistant surface. Polyester composite powder topcoat forms a high gloss and extremely durable finish. Lockable and hinged panel door provides easy access to components.

Montaj

Control panel is mounted on baseframe with steel stand. Located at the right side of the generator set (When you look at the Gen.Set. from Alternator side)

Motor

- Engine speed
- Oil pressure
- Coolant temperature
- Run time
- battery volts
- Configurable timing

Durdurma

- Fail to start
- Emergency stop
- Low oil pressure
- High coolant temperature
- Over /Under speed
- Under/over generator frequency
- Under/over generator voltage
- Oil pressure sensor open
- Coolant temperature sensor open

Uyarılar

- Charge failure
- Battery Low/High voltage
- Fail to stop.
- Low /High generator voltage
- Under /Over generator frequency
- Over /Under speed
- Low oil pressure
- High coolant temperature

Jeneratör

Elektrik Açma

Üretici haber vermeksizin model, teknik özellikler, renk, donanım ve aksesuarlarda değişiklik yapma hakkını saklı tutar.

- Voltage (L-L, L-N)
- Current (L1-L2-L3)
- Frequency
- Gen. Set ready
- Gen. Set enabled

Şebeke

- Mains ready
- Mains enabled

- Generator over current

Opsiyonlar

- Flexible sensor can be controlled with temperature, pressure, percentage (warning/shutdown/electrical trip)
- Local setting parameters and monitoring from PC to control module with USB connection (max 6 mt).

Kontrol Paneli Uyumluluk Listesi

- Electrical Safety / Electro Magenetic Compatibility (EMC)
- BS EN 60950 Electrical Safety
- BS EN 61000-6-2 EMC Generic Immunity Standard
- BS EN 61000-6-4 EMC Generic Emission Standard

Statik Akü Şarj Cihazı

- Battery charger is manufactured with switching-mode and SMD technology and ıt has high efficiency.
- Battery charger models' output V-I characteristic is very close to square and output is 5 amper, 13,8 V for 12 volt and 27,6 V for 24 V . Input 198 - 264 volt AC.
- The charger is fitted with a protection diode across the output.
- Connect charge fail relay coil between positive output and CF output.
- They are equipped with RFI filter to reduce electrical noise radiated from the device.
- Galvanically isolated input and output typically 4kV for high reliability.

Standart Ekipmanlar

- Water cooled, Diesel engine
- Radiator with mechanical fan
- Protective grille for rotating and hot parts
- Electric starter and charge alternator
- Starting battery (with lead acid) including rack and cables
- Engine coolant heater
- Base frame design incorporates an integral fuel tank and anti-vibration isolators
- Flexible fuel connection hoses
- Single bearing, class H alternator
- Industrial exhaust silencer and steel bellows supplied separately(for open sets)
- Static battery charger
- Manual for application and installation

Opsiyonel Ekipmanlar

Motor

- Fuel-Water Seperator Filter
- Oil heater

Alternatör

- Anti-Condensation Heater
- Over sized alternator
- PMG excitation + AVR
- Main line circuit breaker

Üretici haber vermeksizin model, teknik özellikler, renk, donanım ve aksesuarlarda değişiklik yapma hakkını saklı tutar.

Kontrol Paneli

- Automatic synchronising and power control system (Multi gen-set Parallel)
- Parallel system with mains
- Transition synchronization with mains
- Alarm output relays
- Earth fault, single set
- Parallel system with mains
- Remote relay output
- Remote communication with modem
- Charge Ammeter

Transfer Panosu

- Three or four pole contactor
- Three or four pole motor operated circuit breaker

Yardımcı Ekipmanlar

- Main Fuel Tank
- Automatic or manual fuel filling system
- Electrical or manual oil drain pump
- Low and high fuel level alarm
- Inlet and outlet motorized louvers
- Inlet and outlet acoustic baffles
- Tool kit for maintenance
- 1500/3000 hours maintenance kit
- Supplied with oil and coolant (-30°C)

Egzoz

- Residential Silencer
- Silencer Spark Arrester
- Critical Silencer
- Catalytic Convertor

Kabin

- Galvanized Coating
- ISO Container
- Marine Grade Paint

Opsiyonel Alternatör ve Kontrol Paneli

Please contact to your reseller for additional Alternator, Control Panel and Breaker Switch options.

Aksa Sertifikalar

Direktifler

- 2006/42/EC : Machinery Safety Directive
- 2014/30/EU : Electromagnetic Compatibility Directive
- 2014/35/EU : Low Voltage Directive

Standartlar

- TS ISO 8528-5:2022 / TS EN ISO 8528-13:2018 : Reciprocating internal combustion engine-driven alternating current generating sets- Part:13: Safety

Quality Management Systems
ISO 9001:2015
ISO 14001:2015
ISO 45001:2018
ISO 50001:2018
ISO 27001:2013
ISO 10002:2018

Üretici haber vermeksizin model, teknik özellikler, renk, donanım ve aksesuarlarda değişiklik yapma hakkını saklı tutar.