



Introduction

Aksa power generation system, providing optimum performance, and reliability, for stationary standby, prime power, and continuous duty applications. All generator sets are factory build, and production tested.

Power

3 Phase, 50 Hz, PF 0.8

Voltage (V)	STANDBY RATING (ESP)		PRIME RATING (PRP)		STANDBY CURRENT (A)
	kW	kVA	kW	kVA	
400 / 231	59.2	74	54.40	68	107

STANDBY RATING (ESP) Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. ESP is in accordance with ISO 8528-1. Overload is not allowed.

PRIME RATING (PRP) Applicable for supplying power to varying electrical load for unlimited hours. PRP is in accordance with ISO 8528-1. 10 % overload capability is available for a period of 1 hour within 12-hour period of operation.

General Characteristics

Model Name	APB 75A
Frequency (Hz)	50
Fuel Type	Diesel
Engine Make and Model	Aksa A4CRX36TI
Alternator Make and Model	Aksa SC224FS
Control Panel Model	HGM6120CAN
Canopy	ACP 5-PB

Engine Specifications

General Data

Manufacturer	Aksa
Engine Model	A4CRX36TI
Number of Cylinders / Type	4 cylinders - in line
Bore mm (in)	98
Stroke mm (in)	120



Displacement l (cu. In)	3.6
Compression Ratio	17.5:1
Engine Speed (rpm)	1500
Standby Power (kW/hp)	67/89.8
Prime Power (kW/hp)	63/84.5
Block Heater (QTY)	1
Block Heater Power (Watt)	500
Governor System	Mechanic
Air Filter	Dry Type
Aspiration	Turbo Charged

Lubrication System

Oil Capacity l (gal)	10
Max. Oil Temperature °C (F)	130

Fuel System

Fuel Type	Diesel
Injection Type	Direct
Type of Fuel Pump	4JI

Electrical System

Operating Voltage (Vdc)	12 Vdc
Battery and Capacity (Qty/Ah)	1x54

Cooling System

Cooling Method	Water Cooled
Coolant Capacity (engine only) l (gal)	5

Exhaust System

Exhaust Back Pressure in-Hg (kPa)	6
Heat Rejection to Exhaust kW (BTU/min)	52.1

Radiator

Total Coolant Capacity (l)	19.5
Cooling Fan Air Flow m ³ /min (ft ³ /min)	175.2
External Restriction to Cooling Airflow (Pa)	125

Fuel Consumption

Fuel Cons. @100% Prime Load l/h (kg/h)	17.25
--	-------

Alternator Characteristics



Manufacturer	Aksa
Alternator Model	SC224FS
Frequency (Hz)	50
Voltage (V)	400
Phase	3
A.V.R.	MC460B
Voltage Regulation	1
Insulation Class	H
Protection Class	IP23
Rated Power Factor	0,8
Temperature Rise Class	H

Canopy Characteristics

Length mm	2275
Width mm	1008
Height mm	1537
Full Tank Capacity (l)	180

Control Panel

Manufacturer	SmartGen
Control Module Model	HGM6120CAN
Communication Ports	CANBUS



Standard Devices

1. Auto Mains Failure Control Panel

**Panel Equipments:**

- Control with HGM module
- Static battery charger
- Emergency stop push button

A) Generating set control module HGM6120CAN features:

- Configurable via PC software or the front panel
- 5 programmable inputs (configurable for digital or analog signals)
- 4 programmable relay outputs
- Monitors 3-phase generator and mains (utility) voltage
- Event log (50 records)
- Configurable timers and alarm protection thresholds
- Automatic shutdown or alarm upon fault detection
- Supports remote start/stop and load transfer
- Engine pre-heat control (relay output)
- Precision measurement and display of engine and electrical parameters
- Engine total run time accumulation
- Red LED indicators for alarms/shutdown
- LCD display with backlight, supports 8 language interfaces
- Front panel test button
- Modular design, flush mounting

B) Metering via LCD display:

- Generator Voltage (L-L / L-N)
- Generator Current (L1, L2, L3)
- Generator Frequency (Hz)
- Generator Power (Kw)
- Generator Power Factor (COS Φ)
- Accumulated Generator Energy (kWh)
- Load Percentage (%)
- Engine Oil Pressure (kPa / psi / bar)
- Engine Temperature ($^{\circ}\text{C}$ / $^{\circ}\text{F}$)
- Fuel Level (%)
- Battery Voltage (V)
- Charger Voltage (V)
- Mains Voltage (L-L / L-N)

C) Alarms:

- Under Speed / Over Speed
- Under Voltage / Over Voltage
- Under Frequency / Over Frequency
- Overload / Over Current / Overpower
- Low Engine Oil Pressure
- High Engine Coolant Temperature
- Low Fuel Level (Optional)
- Low / High Battery Voltage
- Emergency Stop
- Charge Fail
- Sensor Open Circuit
- Fail to Start
- ECU Communication Failure (for EFI engines)



- Maintenance Due
- Aftertreatment System Related Alarms (for aftertreatment EFI gensets)

2. Power Outlet Terminal Board Mounted on the Gen-set Base Frame

Standard Equipment

High quality, reliable and complete power unit
Compact design

Easy start and maintenance possibility

Every generating set is subject to a comprehensive test program which includes full load testing, checking and provision of all control and safety shut down functions testing

Fully engineered with a wide range of options and accessories: Canopy, sound proof canopy and on-road trailer

Optional Equipment

Engine

Oil heater

Alternator

3/4 Pole Output Circuit Breaker
Anti-condensation Heater

Transfer Panel

Charge ammeter
Transfer Switch 3 Pole
Transfer Switch 4 Pole
Earth Fault, single set

Auxiliary Equipment

Bulk fuel tank
Automatic filling system
Fuel-water separator filter
Low fuel level alarm



Residential silencer
Enclosure or sound proof canopy
Trailer
Manual oil drain pump
Tool kit for maintenance

Aksa Certificates

Directive

- 2006/42/EC : Machinery Safety Directive
- 2014/30/EU : Electromagnetic Compatibility Directive
- 2014/35/EU : Low Voltage Directive

Standarts

- TS ISO 8528-5:2022 / TS EN ISO 8528-13:2018 : Reciprocating internal combustion engine-driven alternating current generating sets- Part:13: Safety

Quality Management Systems

ISO 9001:2015
ISO 14001:2015
ISO 45001:2018
ISO 27001:2013
ISO 10002:2018